

DXLink™ 4K60 HDMI Fiber Receiver Module

DXFP-RX-4K60 (FG1010-565-01)

DXFP-RX-4K60-TAA (FG1010-565-02)



Overview

The DXLink 4K60 Fiber Receiver is HDMI 2.0 and HDCP 2.2 compliant. It supports 4K60 4:4:4 video and High Dynamic Range (HDR) for pixel-for-pixel image reproduction without chroma subsampling. It receives audio, video, control, USB 2.0, and Ethernet over duplex fiber from a DXLink 4K60 Fiber transmitter up to 550 meters away. This module includes a Multi-Mode Duplex (MMD) SFP+ module, which can be replaced with a Single-Mode Duplex (SMD) SFP+ module if needed.

Common Applications

Fiber uses light to distribute data, rather than electric signals making it both the highest quality and most secure way to route video as it is not susceptible to electronic noise or non-intrusive physical wiretapping. This module is compatible with DGX DXLink 4K60 Fiber output cards and DXLink 4K60 Fiber transmitters. It is ideal for applications where the demands of high-resolution video clarity, long distance transmission, and maximum security need to be met without compromise, including campus-wide distribution of sources that are shared between classrooms, secure military applications, casinos, arenas, and museums.

Features

- **4K@60Hz 4:4:4 8bit and HDCP 2.2 with Display Stream Compression (DSC)** - Visually lossless compression and future-proof support.
- **Only one cable** - Receive audio, video, control, USB 2.0, and Ethernet over one optical cable up to 300m for OM3 and 550m for OM4.
- **Industry Leading Data Rate** – DXLink is leading the way with an optical transport rate of 10 Gbps.
- **SmartScale Technology** - Works to automatically recognize any device's supported resolutions and signal type parameters, allowing switching out source and destination devices without manual setup. Also included is the ability to control detailed timing parameters for customized video output formats. (SmartScale is the ability to configure the scaling output by automatically

selecting destination defined resolutions.)

- **Native NetLinX Control Everywhere** – Control connected devices using the built-in IR and RS232 ports.
- **USB 2.0 Pass-Through** – Extend USB 2.0 signals up to 550 meters.

Specifications

GENERAL	
Dimensions (WHD)	220mm x 25mm x 220mm / 8.66" x 0.98" x 8.66"
Weight	Approx. 2.25lb (1.02kg)
Shipping Weight	Approx. 4.14lb (1.88kg)
Mounting Options	Compatible with all V Style versatile mounting options including rack, surface or pole (for V Style Mounting kits, see www.amx.com)
Compatible AMX Products	DXFP-TX-4K60 (FG1010-365-01); DXFP-TX-4K60-TAA (FG1010-365-02); Enova DGX Digital Media Switchers with DGX-O-DXFP-4K60 (FG1061-634) Output Board installed.
Airflow	Convection (openings on top, sides and bottom of case)
Regulatory Compliance	CE/FCC/ETL/PSE/RCM

DXLINK FIBER	
Transport Layer Throughput (max)	10 Gbps
Fiber Connector	LC Duplex conforming to ANSI TIA-EIA 604-10 (FOCIS 10A)
Fiber Transceiver Type	10G SFP+
Optical Cable Type	OM3/OM4
Fiber Cable Length	OM3: 300m/984ft OM4: 550m/1804ft

ACTIVE POWER REQUIREMENTS	
DC Power	DC 12V 3A
Power Consumption (Max)	22.8W
Power Connector	2.1 mm DC power jack

POWER SUPPLY	
External, Included	Each RX ships with a desktop power supply with power cord

ENVIRONMENT	
Temperature (Operating)	0°C to 40°C (32°F to 104°F)
Temperature (Storage)	-20°C to 70°C (4°F to 158°F)
Humidity (Operating)	5% to 85%, non-condensing

BACK CONNECTORS	
Local Power	2.1 mm DC Power Jack
DXLink Fiber Input	LC Duplex conforming to ANSI TIA-EIA 604-10 (FOCIS 10A)
ICS LAN 10/100	RJ-45, TCP/IP Port (ICS LAN 10/100)
HDMI Output	HDMI Type-A Receptacle
Serial	3.5mm Phoenix Receptacle
IR Control	IR RX (3.5mm mini Jack) for IR Receiver IR TX (3.5mm Phoenix Receptacle) for IR Emitter
USB Host	USB Type B Connector ("Host") Connect to a USB-host device (e.g. PC).
USB (HID)	USB Type A Connector ("Device") Connect to USB devices (e.g. keyboard, mouse, interactive whiteboard).
Analog Audio Output	3.5mm Mini Stereo Jack

FRONT INDICATORS, SWITCHES AND BUTTON	
Power Indicator	Green indicates whether or not the device is powered.
Scaler Indicator	Blue indicates the Receiver is programmed and communicating properly
Status Indicator	Green indicates whether or not the Transmitter is programmed and communicating properly.
HDCP Indicator	Yellow LED. On indicates HDCP-protected content is being transmitted, Blinking indicates Non-HDCP Protected content is being transmitted, and Off indicates No content is being transmitted.
LINK Indicator	Green LED. On indicates the ethernet cable is connected and an active link is established, Blinking indicates receiving ethernet data packets.
ID Pushbutton	Place the transmitter in ID mode for setting the NetLinx ID (Device only) and provides additional functionality, such as placing the device in Static IP mode or DHCP Mode.
USB Mode Switch	Switch to USB Host (default setting) or USB Device Mode. Set the switch to Host when connecting to a USB Host such as a PC. Set the switch to Device when connecting to a USB Device such as a keyboard or camera.
DIP Switch	For LAN port, DXLINK, and network control modes configuration.

USB HOST/HID	
USB HOST	USB Type-B Connector. Use when connected with a USB HOST device such as PC. Slide the USB Mode Switch to HOST mode.
USB HID	USB Type-A Connector. Use when connected with USB devices such as a Keyboard & Mouse.

HDMI	
Compatible Formats	HDMI, HDCP
Signal Type Support	HDMI
Input Connector	LC Duplex conforming to ANSI TIA-EIA 604-10 (FOCIS 10A)
Output Signal Type	HDMI
Output Connector	HDMI Type-A Receptacle
Output Scaling	SmartScale [®] , Manual Configuration or Bypass
4K Formats Support	Scaler Mode: 3840x2160@24/25/30/50/60 (4:4:4); 4096x2160@24/25/30/60 (4:4:4) Bypass Mode: 3840x2160@24/25/30/50; 4096x2160@24/25/30; 3840x2160@60 4:4:4; 4096x2160@60 4:2:0
Data Rate (Max)	18Gbps
Pixel Clock (Max)	600MHz
Input Resolution Support	Up to 4K@60Hz, 4:4:4 8bit
Deep Color Support	24-bit, 30-bit. 30-bit supported when the HDMI Output Board scaler or DXLink RX scaler is in Bypass mode using CEA-861 formats and resolution is 2160p30 or less on 4K60 Output products.
Color Space Support	RGB 4:4:4 YCbCr 4:4:4, 4:2:2 and 4:2:0 (4:2:0 requires output scalers to be in bypass) (Input signal support for YCbCr 4:4:4 and 4:2:2, output color-space is converted to RGB 4:4:4 when output scaler is active)
3D Format Support	Not Supported
HDCP Supported	Yes, 1.4, 2.2
Audio Format Support	Bypass Mode: Dolby TrueHD, Dolby Digital, DTS-HD MA, DTS, 2 CH L-

HDMI	
	PCM, 6 CH L-PCM, 8 CH L-PCM Dolby Digital and DTS support up to 48kHz, 5.1 channels Scaler Mode: PCM 2.0
Audio Resolution	16 bit to 24 bit
Audio Sample Rate	32 kHz, 44.1 kHz, 48 kHz, 96 kHz, 192kHz
CEC Support	DXLink out CEC and HDMI local loop out CEC can be switched separately, passthrough HDMI in CEC or controlled by Transmitter.

About AMX by HARMAN

Founded in 1982 and acquired by HARMAN in 2014, AMX® is dedicated to providing AV solutions for an IT World. AMX solves the complexity of managing technology with reliable, consistent and scalable systems comprising control, video switching and distribution, digital signage and technology management. AMX systems are deployed worldwide in conference rooms, classrooms, network operation/command centers, homes, hotels, entertainment venues and broadcast facilities, among others. AMX is part of the HARMAN Professional Group, the only total audio, video, lighting, and control vendor in the professional AV market. HARMAN designs, manufactures and markets premier audio, video, infotainment and integrated control solutions for the automotive, consumer and professional markets. Revised 2021-06-07. ©2021 Harman. All rights reserved. Specifications subject to change.

www.amx.com | +1 469 624 7400 | 800 222 0193